
## Terminal for one-touch adjustment part


## AK series (1000pcs/pack)


- Adjustment parts such as resistor and capacitor can be adjusted without soldering.
- After finishing the adjustment, please solder and fix them.
- Material: Phosphor bronze
- Finish: Tin plating over nickel base
- Printed board fitting hole diameter: φ 0.9
- Leg diameter of a part that can be inserted:  $\phi$  0.3 to  $\phi$  0.8











Part No.: AK-1-1

Part No.: AK-2-1

## For adjustment part

## AM series (10pcs/pack)


- Please use this for fitting an adjustment part such as resistor and capacitor.
- Pitch: 2.54 mm, 20 pins connected
- Possible to cut it neatly by using a nipper for mold cutting (Part number: MOC-3)
- Material Pin: Brass, Finish: Gold plating over nickel base

Resin: PBT (UL94V-0), red

Operating temperature range: -40 to + 125℃



20 pins connected



Part No.	А	В	С	Printed board fitting hole diameter
AM-1-1	0.8	2.5	1.0	φ 0.8
AM-1-2	1.0	5.0	1.5	φ 0.8
AM-1-3	1.0	8.0	1.5	φ 0.8

